

AT4041

Cardioid Condenser End-Address Microphone

40 series studio microphones



Features

- **Specially engineered to meet the most critical acoustic requirements of professional recording, broadcast and sound reinforcement**
- **Smooth, extended frequency response with a slight rise occurring in the high-frequency region**
- **Low-mass diaphragm improves transient response, increases response bandwidth and reduces handling and mechanical noise transfer**
- **Transformerless circuitry virtually eliminates low-frequency distortion and provides superior correlation of high-speed transients**
- **Cardioid polar pattern reduces pickup of sounds from the sides and rear, improving isolation of desired sound source**
- **Rugged turned-brass microphone housing for enduring dependability**
- **Switchable 80Hz high-pass filter minimizes pickup of undesired low-frequency sounds**
- **State-of-the-art design and manufacturing techniques ensure compliance with A-T's stringent consistency and reliability standards**

Description

The AT4041 is a fixed-charge condenser microphone with a cardioid polar pattern. It is designed to meet the demands of critical studio and live applications.

The microphone requires 48V phantom power for operation.

The cardioid polar pattern of the microphone is more sensitive to sound originating directly in front of the element, making it useful for controlling feedback and reducing pickup of unwanted sounds.

The output of the microphone is a 3-pin XLRM-type connector.

A switch permits choice of flat response or low-frequency roll-off (via integral 80 Hz high-pass filter) to help control undesired ambient noise.

The microphone is enclosed in a rugged housing. The included AT8405a stand clamp permits mounting on any microphone stand with $\frac{5}{8}$ "-27 threads. A windscreen and a protective carrying case are also included.

Operation and Maintenance

The AT4041 requires 48V phantom power for operation.

Output is low impedance (Lo-Z) balanced. The signal appears across Pins 2 and 3; Pin 1 is ground (shield). Output phase is "Pin 2 hot"—positive acoustic pressure produces positive voltage at Pin 2.

To avoid phase cancellation and poor sound, all mic cables must be wired consistently: Pin 1-to-Pin 1, etc.

An integral 80 Hz high-pass filter provides easy switching from a flat frequency response to a low-end roll-off. The roll-off position reduces the pickup of low-frequency ambient noise (such as traffic, air-handling systems, etc.), room reverberation and mechanically coupled vibrations. To engage the high-pass filter, slide the switch toward the "bent" line.

Avoid leaving the microphone in the open sun or in areas where temperatures exceed 110° F (43° C) for extended periods. Extremely high humidity should also be avoided.

To reduce the environmental impact of a multi-language printed document, product information is available online at www.audio-technica.com in a selection of languages.

Afin de réduire l'impact sur l'environnement de l'impression de plusieurs langues, les informations concernant les produits sont disponibles sur le site www.audio-technica.com dans une large sélection de langue.

Para reducir el impacto al medioambiente, y reducir la producción de documentos en varios leguajes, información de nuestros productos están disponibles en nuestra página del Internet: www.audio-technica.com.

Para reduzir o impacto ecológico de um documento impresso de várias línguas, a Audio-Technica providência as informações dos seus produtos em diversas línguas na www.audio-technica.com.

Per evitare l'impatto ambientale che la stampa di questo documento determinerebbe, le informazioni sui prodotti sono disponibili online in diverse lingue sul sito www.audio-technica.com.

Der Umwelt zuliebe finden Sie die Produktinformationen in deutscher Sprache und weiteren Sprachen auf unserer Homepage: www.audio-technica.com.

Om de gevolgen van een gedrukte meertalige handleiding op het milieu te verkleinen, is productinformatie in verschillende talen "on-line" beschikbaar op: www.audio-technica.com.

本公司基於減少對環境的影響，將不作多語言文件的印刷，有關產品訊息可在 www.audio-technica.com 的官方網頁上選擇所屬語言及瀏覽。

本公司基于减少对环境的影响，将不作多语言文档的印刷，有关产品信息可在 www.audio-technica.com 的官方网页上选择所属语言和浏览。

자원절약, 환경보호를 위해 국문 사용 설명서는 인쇄하지 않았습니다. 제품정보는 www.audio-technica.com 에서 원하는 언어 선택 후에 다운로드 받으실 수 있습니다.

Specifications

Element	Fixed-charge back plate, permanently polarized condenser
Polar pattern	Cardioid
Frequency response	20-20,000 Hz
Low frequency roll-off	80 Hz, 12 dB/octave
Open circuit sensitivity	-36 dB (15.8 mV) re 1V at 1 Pa
Impedance	100 ohms
Maximum input sound level	145 dB SPL, 1 kHz at 1% T.H.D.
Dynamic range (typical)	121 dB, 1 kHz at Max SPL
Signal-to-noise ratio¹	70 dB, 1 kHz at 1 Pa
Phantom power requirements	48V DC, 3.2 mA typical
Switch	Flat, roll-off
Weight	120 g (4.2 oz)
Dimensions	159.5 mm (6.28") long, 21.0 mm (0.83") diameter
Output connector	Integral 3-pin XLRM-type
Audio-Technica case style	S1
Accessories furnished	AT8405a stand clamp for 5/8"-27 threaded stands; AT8159 windscreen; protective carrying case

In the interest of standards development, A.T.U.S. offers full details on its test methods to other industry professionals on request.


1 Pascal = 10 dynes/cm² = 10 microbars = 94 dB SPL

¹ Typical, A-weighted, using Audio Precision System One.

Specifications are subject to change without notice.




frequency response: 20–20,000 Hz



LEGEND — 12" or more on axis
--- Roll-off

polar pattern



LEGEND — 200 Hz
--- 1 kHz
..... 5 kHz
- - - 8 kHz

 **audio-technica**

Audio-Technica Corporation
audio-technica.com ©2013 Audio-Technica